



Computerized Alternator Tester ALT-98

Features:

- Fully automated precise testing for high volume applications at the touch of a button
- Measures over 100 different alternator parameters
- User configurable Pass and Fail printed reports and labels through a PC and the ALT Report program for virtually unlimited flexibility, or directly to a printer interface from the tester, both can include performance curve, oscilloscope pattern, and test results
- Learning Mode records sample test results for easy setup of test specifications in just minutes
- Checks all types of alternator and voltage regulator terminals and functions such as computer control, soft start delay, feedback, under/over voltage indication, PCM control, load response control, tachometer frequency
- Simulates all signals to the alternator including on-board computer functions
- Measures turn on speed, ripple current, pulley size, input power, voltage regulator instability, stator voltage, reverse diode leakage, can test rectifier voltage drop, regulator saturation voltage, and torque and efficiency (optional)
- 10HP computer controlled variable speed motor with high reliability Mitsubishi motor drive
- User configurable test procedures with test time from 10 to 60 seconds
- Measures full output performance curve in 15 seconds
- Large LCD screen for viewing test results, performance curves, and manual mode operation
- Computer controlled 360 Amp load bank 6 - 42 Volt with resolution of 0.1V @ 12V
- Endurance test mode for component validation
- Test result statistics can be recorded for SPC or analysis



- Test spec database editor for windows
- Includes universal harness and regulator test plugs for popular applications
- Built-in calibration, automatic diagnostic, manual, and detailed report test modes
- Available in many working voltages (220 to 480V at 50/60 Hz).
- Built in battery simulator 6-42V for consistent test conditions

Technical Data Measured Parameters:

Output voltage	0-50 ± 0.15%	Alternator leakage	0-100 mA ± 1%
Stator voltage	0-50 ± 0.15%	Feedback voltage	0-50V (0-100% PWM) ± 0.15%
Output current	0-300 A ± 0.15%	Output power	0-10000W ± 0.3%
Field current	0-10A ± 1%	Memory for 4000 part number profiles	
Alternator speed	0-12000 RPM ± 1%	Alternator temperature	25-200 °C 1% (option)

D&V Electronics Ltd. 130 Zenway Boulevard • Woodbridge • Ontario • Canada • L4H 2Y7

Tel: (905) 264-7646 • Fax: (905) 264-0502 • Tech Support 1-888-979-1919

www.dvelectronics.com